

# BDC 0.1 ... 2.5 GHz

## Directional Coupler

### STANDARD MODELS

Model	Frequency Range X)	Coupling X) dB	Power P <sub>min</sub> W	Insertion Loss max dB	Directivity min dB	VSWR max Main Line	Main Line Connector 1), 2)	Coupling Line Connector 3)
BDC 0125-20/200	100 ... 2500 MHz	20 ±2.75	200	0.8	15	1.25:1	N-f	SMA-f

S: Single directional coupler

### OPTIONS

1) male RF input connector

2) alternative main line connectors

X) custom frequency range and custom coupling attenuation upon request

\*) WRD 650: below 6.2 GHz, VSWR and directivity deteriorate

#### Notice:

Under normal operating conditions all Directional Couplers do not need to be mounted to a heatsink. However, if the units permanently run into high mismatch conditions at full rated power, the circuits will heat up significantly. In this case, we would recommend the units be mounted to a suitable heatsink or metal surface, capable to maintain a baseplate temperature of +60°C max.