

STANDARDMODELLE

Modell	Frequenzbereich	Leistung P _{min} W	Kopplung X) dB	Dämpfung max dB	Unebenheit max dB	Richtschärfe min dB	VSWR max Hauptarm	Hauptarm Stecker 1), 2)	Koppelarm Stecker 3)
BDC 0110-60/10000	9 kHz ... 100 MHz	10000	60 ±1	0,1	±1	20	1.3:1	1 5/8" EIA	SMA-f
BDC 0110-70/10000	9 kHz ... 100 MHz	10000	70 ±1	0,1	±1	20	1.3:1	1 5/8" EIA	SMA-f
BDC 0125-30/100	9 kHz ... 250 MHz	100	30 ±1	0,8	±0,8	20	1.25:1	N-f	SMA-f
BDC 0125-30/250	9 kHz ... 250 MHz	250	30 ±1	0,8	±0,5	20	1.25:1	N-f	SMA-f
BDC 0125-40/100	9 kHz ... 250 MHz	100	40 ±1	0,5	±0,5	20	1.1:1	N-f	SMA-f
BDC 0125-40/250	9 kHz ... 250 MHz	250	40 ±1	0,5	±0,5	20	1.1:1	N-f	SMA-f
BDC 0125-40/500	9 kHz ... 250 MHz	500	40 ±1	0,4	±0,75	20	1.25:1	N-f	SMA-f
BDC 0125-50/1000	9 kHz ... 250 MHz	1000	50 ±1	0,4	±0,75	20	1.25:1	N-f	SMA-f
BDC 0125-50/2000	9 kHz ... 250 MHz	2000	50 ±1	0,15	±1	20	1.15:1	N-f	SMA-f
BDC 0125-50/3000	9 kHz ... 250 MHz	3000	50 ±1	0,15	±0,5	20	1.2:1	7-16-f	SMA-f
BDC 0125-60/5000	9 kHz ... 250 MHz	5000	60 ±1	0,1	±1	20	1.3:1	1 5/8" EIA	SMA-f
BDC 0125-70/10000	9 kHz ... 250 MHz	10000	70 ±1	0,1	±1	20	1.2:1	1 5/8" EIA	SMA-f
BDC 0140-30/250	9 kHz ... 400 MHz	250	30 ±1	0,75	±0,5	20	1.2:1	N-f	SMA-f
BDC 0140-40/200	9 kHz ... 400 MHz	200	40 ±1	0,5	±0,5	20	1.25:1	N-f	SMA-f
BDC 0140-40/500	9 kHz ... 400 MHz	500	40 ±1	0,5	±0,5	20	1.3:1	N-f	SMA-f
BDC 0140-50/500	9 kHz ... 400 MHz	500	50 ±1	0,5	±0,5	20	1.3:1	N-f	SMA-f
BDC 0150-30/100	9 kHz ... 500 MHz	100	30 ±1	0,8	±0,5	20	1.25:1	N-f	SMA-f
BDC 0100-30/50	9 kHz ... 1000 MHz	50	30 ±1	1,2	±0,5	20	1.3:1	N-f	SMA-f
BDC 0100-40/100	9 kHz ... 1000 MHz	100	40 ±1	0,6	±0,5	20	1.3:1	N-f	SMA-f
BDC 0100-40/200	9 kHz ... 1000 MHz	200	40 ±1	0,6	±0,5	20	1.3:1	N-f	SMA-f
BDC 0100-40/500	9 kHz ... 1000 MHz	500	40 ±1	0,45	±0,5	20	1.3:1	N-f	SMA-f
BDC 0100-43/700	9 kHz ... 1000 MHz	700	43 ±1	0,45	±0,5	20	1.3:1	7-16-f	SMA-f
BDC 0100-43/1000	9 kHz ... 1000 MHz	1000	43 ±1	0,45	±0,5	20	1.3:1	7-16-f	SMA-f
BDC 0100-50/500	9 kHz ... 1000 MHz	500	50 ±1	0,45	±0,5	20	1.3:1	N-f	SMA-f
BDC 0100-50/1000	9 kHz ... 1000 MHz	1000	50 ±1	0,45	±0,5	25	1.3:1	SC-f	SMA-f
BDC 0125-50/1000	0,1 ... 250 MHz	1000	50 ±1	0,15	±0,5	20	1.15:1	N-f	SMA-f

BDC 9 kHz ... 1000 MHz Richtkoppler

Modell	Frequenzbereich	Leistung Pmin W	Kopplung X) dB	Dämpfung max dB	Unebenheit max dB	Richtschärfe min dB	VSWR max Hauptarm	Hauptarm Stecker 1), 2)	Koppelarm Stecker 3)
BDC 0110-40/200	0,1 ... 1000 MHz	200	40 ±1	0,6	±0,5	20	1.3:1	N-f	SMA-f
BDC 0110-40/500	0,1 ... 1000 MHz	500	40 ±1	0,5	±0,5	20	1.25:1	N-f	SMA-f
BDC 0103-40/1000	1 ... 30 MHz	1000	40 ±1	0,1	±0,25	25	1.05:1	N-f	SMA-f
BDC 0103-50/1500	1 ... 30 MHz	1500	50 ±1	0,2	±0,5	20	1.15:1	N-f	SMA-f
BDC 0103-60/15000	1 ... 30 MHz	15000	60 ±1	0,05	±0,5	25	1.1:1	1 5/8" EIA	N-f
BDC 0101-30/100	1 ... 100 MHz	100	30 ±1	0,5	±0,5	20	1.25:1	N-f	SMA-f
BDC 0101-40/100	1 ... 100 MHz	100	40 ±1	0,5	±0,5	20	1.15:1	N-f	SMA-f
BDC 0101-50/1500	1 ... 100 MHz	1500	50 ±1	0,15	±1	20	1.2:1	N-f	SMA-f
BDC 0101-70/10000	1 ... 100 MHz	1500	70 ±1	0,05	±1	20	1.2:1	1 5/8" EIA	SMA-f
BDC 0110-20/50S	1 ... 1000 MHz	50	20 ±1	1,4	±1	20	1.3:1	N-f	SMA-f
BDC 0120-30/50	1 ... 2000 MHz	50	30 ±1	1,25	±1	18	1.35:1	SMA-f	SMA-f
BDC 0103-40/500	1,5 ... 30 MHz	500	40 ±1	0,1	±0,25	25	1.3:1	N-f	SMA-f
BDC 0103-40/2500	1,5 ... 30 MHz	2500	40 ±1	0,1	±0,25	25	1.05:1	7-16-f	SMA-f
BDC 0103-50/5000	1,5 ... 30 MHz	5000	50 ±1	0,05	±0,3	25	1.10:1	N-f	SMA-f
BDC 1001-50/1000	10 ... 100 MHz	1000	50 ±1	0,1	±0,25	20	1.1:1	N-f	SMA-f
BDC 1001-50/1200	10 ... 175 MHz	1200	50 ±1	0,1	±0,25	20	1.1:1	N-f	SMA-f
BDC 1002-60/10000	10 ... 200 MHz	10000	60 ±1	0,1	±0,5	25	1.1:1	1 5/8" EIA	SMA-f
BDC 1005-70/10000	10 ... 500 MHz	10000	70 ±1	0,2	±0,75	20	1.3:1	1 5/8" EIA	SMA-f
BDC 1010-30/50	10 ... 1000 MHz	50	30 ±1	1	±0,5	20	1.3:1	N-f	SMA-f
BDC 0210-40/1500	20 ... 100 MHz	1500	40 ±1	0,1	±0,5	20	1.15:1	N-f	SMA-f
BDC 0213-50/2000	20 ... 130 MHz	2000	50 ±1	0,1	±0,5	20	1.05:1	N-f	SMA-f
BDC 0213-60/3000	20 ... 130 MHz	3000	60 ±1	0,15	±0,5	20	1.2:1	7-16-f	SMA-f
BDC 0213-60/7000	20 ... 130 MHz	7000	60 ±1	0,1	±0,5	25	1.15:1	1 5/8" EIA	SMA-f
BDC 0213-60/10000	20 ... 130 MHz	10000	60 ±1	0,1	±0,5	25	1.15:1	1 5/8" EIA	SMA-f
BDC 0250-20/100	20 ... 500 MHz	100	20 ±1	0,7	±1	20	1.3:1	N-f	SMA-f
BDC 0250-40/100	20 ... 500 MHz	100	40 ±1	0,4	±0,5	20	1.25:1	N-f	SMA-f
BDC 0250-40/200	20 ... 500 MHz	200	40 ±1	0,4	±0,5	20	1.25:1	N-f	SMA-f
BDC 0250-50/750	20 ... 500 MHz	750	50 ±1	0,3	±0,5	20	1.2:1	N-f	SMA-f

BDC 9 kHz ... 1000 MHz Richtkoppler

Modell	Frequenzbereich	Leistung	Kopplung	Dämpfung	Unebenheit	Richtschärfe	VSWR	Hauptarm	Koppelarm
		P _{min} W	X) dB	max dB	max dB	min dB	max Hauptarm	Stecker 1), 2)	Stecker 3)
BDC 0250-50/1500	20 ... 500 MHz	1500	50 ±1	0,3	±0,5	20	1.2:1	N-f	SMA-f
BDC 0250-60/1500	20 ... 500 MHz	1500	60 ±1	0,15	±0,5	20	1.2:1	N-f	SMA-f
BDC 0210-30/100	20 ... 1000 MHz	100	30 ±1	0,7	±0,5	20	1.25:1	SMA-f	SMA-f
BDC 0210-30/150	20 ... 1000 MHz	150	30 ±1	0,8	±0,5	20	1.3:1	N-f	SMA-f
BDC 0210-40/150	20 ... 1000 MHz	150	40 ±1	0,35	±0,5	20	1.25:1	SMA-f	SMA-f
BDC 0210-40/500	20 ... 1000 MHz	500	40 ±1	0,35	±0,5	20	1.25:1	N-f	SMA-f
BDC 0210-53/1200	20 ... 1000 MHz	1200	53 ±1	0,4	±1	20	1.3:1	7-16-f	SMA-f
BDC 0210-63/25	20 ... 1000 MHz	25	63 ±1,5	0,2	±1,5	20	1.3:1	N-f	SMA-f
BDC 0250-40/100	20 ... 5000 MHz	100	40 ±1	0,35	±0,25	20	1.3:1	N-f	SMA-f
BDC 0325-43/100	30 ... 2500 MHz	100	43 ±1	0,35	±1,75	18	1.25:1	N-f	SMA-f
BDC 0325-50/200	30 ... 2500 MHz	200	50 ±1	0,25	±1	20	1.2:1	N-f	SMA-f
BDC 0850-60/5000	80 ... 500 MHz	5000	60 ±1	0,15	±0,5	20	1.2:1	1 5/8" EIA	N-f
BDC 0810-40/200	80 ... 1000 MHz	200	40 ±1	0,2	±0,3	20	1.2:1	N-f	SMA-f
BDC 0810-40/500	80 ... 1000 MHz	500	40 ±1	0,2	±0,3	20	1.1:1	N-f	SMA-f
BDC 0810-50/1500	80 ... 1000 MHz	1500	50 ±1	0,1	±0,3	20	1.2:1	N-f	SMA-f
BDC 0810-50/2500	80 ... 1000 MHz	2500	50 ±1	0,1	±0,3	20	1.2:1	7-16-f	SMA-f
BDC 0810-60/2500	80 ... 1000 MHz	2500	60 ±1	0,1	±0,5	20	1.3:1	7-16-f	SMA-f
BDC 0810-60/5000	80 ... 1000 MHz	5000	60 ±1	0,2	±0,5	20	1.25:1	1 5/8" EIA	SMA-f
BDC 0810-60/10000	80 ... 1000 MHz	10000	60 ±1	0,2	±0,5	20	1.25:1	1 5/8" EIA	SMA-f
BDC 0830-60/200	80 ... 3000 MHz	200	60 ±1	0,25	±1	20	1.25:1	N-f	N-f
BDC 2010-20/200	200 ... 1000 MHz	200	20 ±1	0,2	±0,75	20	1.20:1	SMA-f	SMA-f
BDC 4010-60/5000	400 ... 1000 MHz	5000	60 ±1	0,1	±0,5	20	1.15:1	1 5/8" EIA	SMA-f

OPTIONEN

- 1) Männlicher Stecker am HF-Eingang
- 2) Andere Steckerart am Hauptarm
- 3) N-f Stecker an den Koppelports
- X) Spezielle Frequenzbereiche und Koppeldämpfungen auf Anfrage