

# BDC 1 ... 6 GHz Directional Coupler

## STANDARD MODELS

Model	Frequency Range X)	Power P <sub>min</sub> W	Coupling X) dB	Insertion Loss max dB	Directivity min dB	VSWR max Main Line	Main Line Connector 1), 2)	Coupling Line Connector 3)
BDC 1060-20/200	1 ... 6 GHz	200	20 ±1	0.3	20	1.4:1	N-f	SMA-f
BDC 1060-30/500	1 ... 6 GHz	500	30 ±1	0.2	20	1.3:1	N-f	SMA-f
BDC 1060-40/500	1 ... 6 GHz	500	40 ±1	0.2	20	1.3:1	N-f	SMA-f
BDC 1060-40/1300	1 ... 6 GHz	1300	40 ±1	0.2	20	1.3:1	7-16-f	SMA-f
BDC 1060-50/500	1 ... 6 GHz	500	50 ±1	0.2	20	1.3:1	N-f	SMA-f
BDC 1060-50/1300	1 ... 6 GHz	1300	50 ±1	0.2	20	1.3:1	7-16-f	SMA-f

For individual data sheets, please click on the above model name

Dimensions without connectors