

BDC 20 ... 130 MHz Directional Coupler

STANDARD MODELS

Model	Frequency Range X)	Coupling X) dB	Power P _{min} W	Insertion Loss max dB	Directivity min dB	VSWR max Main Line	Main Line Connector 1), 2)	Coupling Line Connector 3)
BDC 0213-50/2000	20 ... 130 MHz	50 ±1.5	2000	0.1	20	1.05:1	N-f	SMA-f
BDC 0213-60/3000	20 ... 130 MHz	60 ±1.5	3000	0.15	20	1.2:1	7-16-f	SMA-f
BDC 0213-60/7000	20 ... 130 MHz	60 ±1.5	7000	0.1	25	1.15:1	1 5/8" EIA	SMA-f
BDC 0213-60/10000	20 ... 130 MHz	60 ±1.5	10000	0.1	25	1.15:1	1 5/8" EIA	SMA-f

For individual data sheets, please click on the above model name

S: Single directional coupler

Notice:

Under normal operating conditions all Directional Couplers do not need to be mounted to a heatsink. However, if the units permanently run into high mismatch conditions at full rated power, the circuits will heat up significantly. In this case, we would recommend the units be mounted to a suitable heatsink or metal surface, capable to maintain a baseplate temperature of +60°C max.