

BDC 500 MHz ... 3 GHz

Directional Coupler

STANDARD MODELS

| Model | Part Number | Frequency Range | Coupling dB | Power Pmin W | Insertion Loss max dB | Directivity min dB | VSWR max Main Line | Main Line Connectors | Coupling Line Connector(s) |
|-----------------|-------------|-------------------|----------------|--------------------|-----------------------------|--------------------------|--------------------------|-------------------------|-------------------------------|
| BDC 0530-30/500 | 10019143 | 500 MHz ... 3 GHz | 30 ±2.35 | 500 | 0.2 | 20 | 1.2:1 | N-f/N-f | SMA-f |
| BDC 0530-40/500 | 10019144 | 500 MHz ... 3 GHz | 40 ±2.35 | 500 | 0.2 | 20 | 1.2:1 | N-f/N-f | SMA-f |
| | 10020995 | 500 MHz ... 3 GHz | 40 ±2.3 | 500 | 0.2 | 20 | 1.3:1 | N-m/N-f | SMA-f |
| BDC 0530-50/500 | 10019145 | 500 MHz ... 3 GHz | 50 ±1.75 | 500 | 0.2 | 20 | 1.3:1 | N-f/N-f | SMA-f |

For individual data sheets, please click on the above model name