

STANDARD MODELS

Model	Frequency Range	Output Power $P_N$ min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
BLMA 1826-0.25	18 ... 26.5 GHz	0.25 / 0.28	24 / 26 ±2	20 / 20	50	2 HU, 430 mm	9
BLMA 1826-0.5	18 ... 26.5 GHz	0.5 / 0.6	27 / 29 ±2	20 / 20	50	2 HU, 430 mm	9
BLMA 1826-0.7	18 ... 26.5 GHz	0.7 / 0.8	28.5 / 31 ±2	20 / 20	50	2 HU, 430 mm	9
BLMA 1826-1	18 ... 26.5 GHz	1 / 1.1	30 / 32 ±2	20 / 20	50	2 HU, 430 mm	9
BLMA 1826-2	18 ... 26.5 GHz	2 / 2.2	33 / 35 ±2	20 / 20	75	2 HU, 430 mm	9
BLMA 1826-3	18 ... 26.5 GHz	3 / 3.3	34.8 / 38 ±3	20 / 20	120	2 HU, 430 mm	10
BLMA 1826-4	18 ... 26.5 GHz	4 / 4.4	36 / 40 ±4	20 / 20	150	2 HU, 430 mm	11
BLMA 1826-5	18 ... 26.5 GHz	5 / 6	37 / 41 ±4	20 / 20	150	2 HU, 430 mm	12
BLMA 1826-10	18 ... 26.5 GHz	10 / 12	40 / 43 ±3	20 / 20	200	2 HU, 430 mm	12
BLMA 1826-20	18 ... 26.5 GHz	20 / 22	43 / 47 ±4	20 / 20	400	3 HU, 630 mm	16
BLMA 1826-40	18 ... 26.5 GHz	40 / 44	46 / 50 ±4	20 / 20	600	3 HU, 630 mm	22
BLMA 1826-50	18 ... 26.5 GHz	50 / 55	47 / 51 ±4	20 / 20	800	4 HU, 630 mm	32
BLMA 1826-70	18 ... 26.5 GHz	70 / 77	48.5 / 53 ±4	20 / 20	1000	4 HU, 630 mm	32
BLMA 1826-100	18 ... 26.5 GHz	100 / 110	50 / 54 ±4	20 / 20	1500	4 HU, 630 mm	32
BLMA 1826-150	18 ... 26.5 GHz	150 / 160	51.8 / 57 ±5	20 / 20	2500	5 HU, 630 mm	35
BLMA 1826-200	18 ... 26.5 GHz	200 / 220	53 / 58 ±5	20 / 20	2800	5 HU, 630 mm	35

For individual data sheets, please click on the above model name

1 HU = 44.45 mm