

STANDARD MODELS

| Model | Frequency Range | Output Power P_N min / typ W | Gain min / typ dB | Harmonics 2nd / 3rd dBc | Line Power VA | Dimensions (H, D) 19"-System | Weight kg |
|---------------|---|--------------------------------------|--------------------------|-------------------------------|------------------|------------------------------------|--------------|
| BLMA 2640-0.1 | 26.5 ... 40 GHz | 0.1 / 0.12 | 20 / 23 ±3 | 20 / 20 | 50 | 2 HU, 430 mm | 9 |
| BLMA 2640-0.2 | 26.5 ... 40 GHz | 0.2 / 0.23 | 23 / 26 ±3 | 20 / 20 | 50 | 2 HU, 430 mm | 9 |
| BLMA 2640-0.3 | 26.5 ... 40 GHz | 0.3 / 0.35 | 25 / 28 ±3 | 20 / 20 | 90 | 2 HU, 430 mm | 9 |
| BLMA 2640-0.5 | 26.5 ... 40 GHz | 0.5 / 0.6 | 27 / 30 ±3 | 20 / 20 | 90 | 2 HU, 430 mm | 10 |
| BLMA 2640-0.8 | 26.5 ... 40 GHz | 0.8 / 1 | 29 / 32 ±3 | 20 / 20 | 90 | 2 HU, 430 mm | 10 |
| BLMA 2640-1 | 26.5 ... 40 GHz | 1 / 1.1 | 30 / 34 ±4 | 20 / 20 | 110 | 2 HU, 430 mm | 11 |
| BLMA 2640-1.5 | 26.5 ... 40 GHz | 1.5 / 1.6 | 31.8 / 36 ±4 | 20 / 20 | 120 | 2 HU, 430 mm | 12 |
| BLMA 2640-2 | 26.5 ... 40 GHz 26.5 ... 36 GHz 36 ... 40 GHz | 2 / 2.1 1.6 / 1.8 | 33 / 37 ±4 32 / 36 ±4 | 20 / 20 20 / 20 | 150 | 2 HU, 430 mm | 12 |
| BLMA 2640-4D | 26.5 ... 40 GHz 26.5 ... 31 GHz 31 ... 40 GHz | 4 / 4.5 4 / 4.25 | 36 / 40 ±4 36 / 40 ±4 | 20 / 20 20 / 20 | 300 | 2 HU, 430 mm | 13 |
| BLMA 2640-5 | 26.5 ... 40 GHz | 5 / 5.5 | 37 / 41 ±4 | 20 / 20 | 300 | 2 HU, 430 mm | 13 |
| BLMA 2640-8 | 26.5 ... 40 GHz | 8 / 9 | 39 / 43 ±4 | 20 / 20 | 300 | 2 HU, 430 mm | 13 |
| BLMA 2640-10 | 26.5 ... 40 GHz | 10 / 11 | 40 / 44 ±4 | 20 / 20 | 400 | 2 HU, 430 mm | 13 |
| BLMA 2640-20 | 26.5 ... 40 GHz | 20 / 22 | 43 / 47 ±4 | 20 / 20 | 800 | 3 HU, 630 mm | 22 |

For individual data sheets, please click on the above model name

1 HU = 44.45 mm