

BDC 9 kHz ... 100 MHz

Directional Coupler

STANDARD MODELS

| Model | Part Number | Frequency Range | Coupling dB | Power Pmin W | Insertion Loss max dB | Directivity min dB | VSWR max Main Line | Main Line Connectors | Coupling Line Connector(s) |
|-------------------|-------------|-------------------|----------------|--------------------|-----------------------------|--------------------------|--------------------------|-------------------------|-------------------------------|
| BDC 0110-60/10000 | 10014900 | 9 kHz ... 100 MHz | 60 ±1 | 10000 | 0.1 | 20 | 1.3:1 | 1 5/8"/1 5/8" | SMA-f |
| BDC 0110-70/10000 | 10008106 | 9 kHz ... 100 MHz | 70 ±1 | 10000 | 0.1 | 20 | 1.2:1 | 1 5/8"/1 5/8" | SMA-f |
| | 10016830 | 9 kHz ... 100 MHz | 70 ±2 | 1000 | 0.1 | 20 | 1.3:1 | 1 5/8"/1 5/8" | N-f |

For individual data sheets, please click on the above model name